



Assembly

It is recommended that the installation be carried out by a specialist company. We ask for your understanding that we can only assume a warranty if properly installed.

ATTENTION!

Before installation, the connecting cable must be de-energized.

Note

The distance to the ceiling, as well as other objects z. B. to a table under the light, must be at least 0.5m each.

Attach the mounting plate to the ceiling with dowel and screw.

Determine the pendulum lengths of the individual luminaires and shorten the cables upon need.

TIP! To prevent the cable from splitting when wrapping the cable with "Tesa" tape around the separation point and separate the jacket exactly on the tape.

1. Feed the supply cables through the openings of the cover plate and clamp the cable ends under the strain relief.
2. Connect the lamp cable to the supply cable. Make sure that the protective conductor (green / yellow) is placed on the ground terminal.
3. Slide the cover onto the mounting plate. The cover plate is held by a magnet.
4. The luminaire may only be operated when fully assembled.

Ball and lamp mounting

- (1) Screw the first ring onto the socket. Pay attention to the position of the ring collar.
- (2) Slide the ball holder over the socket and fix the ball holder to the second ring. Pay attention to the ring collar (see left). Hand-tighten the ring. Do not use a tool!
- (3) First push the ball with one opening over two wire arms. Then turn the ball so that the other two wire arms in the ball disappear.
- (4) Lift the ball slightly and position the ball as needed. Lower the ball so that it is held by the four arms.
- (5) Insert the bulb.

dimming

The light is dimmable, depending on the light source. Please read the instructions of the illuminant manufacturer.

cleaning

It is recommended to clean the lamp with a soft, dry cloth.

